

260-400 GHz Fixed Attenuator
固定衰减器
描述Description

The LFA-6005 is a waveguide fixed attenuator which operates between 260 and 400 GHz.

特点Feature

- Frequency Range: 260-400 GHz
- Attenuation Range: 0-40 dB

产品规格Specifications	
RF频率RF Frequency [GHz]	260 - 400
衰减范围Attenuation Range [dB]	0 - 40可选
驻波VSWR	> 1.6@40dB
RF输入功率RF Input Power [dBm]	20
RF接口RF Port	WR2.8(UG387/UM)
工作温度Operation Temperature[°C]	+18 ~ +28
储存温度Storage Temperature[°C]	-40 ~ +70

外形尺寸Overall Dimension
