

325-500 GHz Frequency Multiplier

倍频器

描述Description

The LMA-6014 is a fullband frequency multiplier which can output frequency of 325-500 GHz.

特点Feature

- Input Frequency: 108.33-166.67 GHz
- Multiplication Factor: 3

产品规格Specifications

输入频率Input Frequency [GHz]	108.33 - 166.67
输出频率Output Frequency [GHz]	325 - 500
倍频次数Multiplication Factor	3
输入功率Input Power [dBm]	+14
输出功率Output Power [dBm]	-8 Typ.
输入连接器口RF Input Port	WR6.5(UG387/UM)
输出连接器口RF Output Port	WR2.2(UG387/UM)
最大壳温Max. Case Temperature[°C]	+45